

# XVA-202



## 2 x 2 VGA Matrix w/Audio & IR / Serial Control

### ► Specifications

		XVA-202
Input Port	Video	HDB15-F x 2
	Audio	3.5mm Stereo Jack x 2
Output Port	Video	HDB15-F x 2
	Audio	3.5mm Audio Jack x 2
LED	Port Selection	4
Control	Push Button	2
	Serial	DB9-F (DCE) x 1
	Remote	Remote Control Sensor
EDID Copy Button		x 1
Resolution (max.)		Full HD 1080p (1920 x 1080), WUXGA (1920 x 1200)
Power Supply (min.)		DC 9-12V, 0.3A
Enclosure		Metal
H x W x D		40 x 160 x 100
Weight (g)		600

### ► Features

- Routes 2 different VGA video and audio sources to 2 different VGA monitors and speakers.
- Supports
  1. Button front panel control
  2. IR remote control
  3. Serial control
- Front buttons designed for easy switching
- EDID Copy function ensures accurate output display
- Switches both of the video and audio directly
- Each input can be independently connected to any or all outputs.
- Supports the video resolution of WUXGA (1920 x 1200) / Full HD (1920x 1080) / UXGA (1600x 1200)
- Compatible with most of the popular screen resolution to XGA, SXGA, UXGA, WSXGA ....Full HD, WUXGA system

### ► Connection Pattern

