

MAAG-112 MAAG-114



2/4-Port HDMI KVM Switch w/ Audio & Hotkey Control

► Specifications

		MAAG-112	MAAG-114
Console Port		1	
Computer Port		2	4
Front Panel Push Button		1	4
Automatic Scan Interval		3, 8, 15, 30 Seconds	
Cable Length (Max)		3M (10ft) for USB	
Computer ON-LINE LED		2	4
Computer Selected LED		2	4
Hot Plug-and-Play		Yes	
Console Interface	USB Port	4 (KB+MS+Extra USB 2.0)	
	KB	USB	
	MS	USB	
	Monitor	HDMI	
	Audio Jack (Speaker+Mic)	1 Set	
Computer Interface	KB	USB	
	MS		
	Monitor	HDMI	
	Audio Jack (Speaker+Mic)	2 Set	4 Set
HDCP Support		Yes	
Hotkey		Yes	
OSD		No	
Resolution		1920 x 1200	
DDC2B		Yes	
H x W x D (mm)		40 x 160 x 100	44 x 220 x 130

► Features

- Support USB console
- 2/4 computers share 4 different USB peripherals (KB + MS + USB 2.0 Devices)
- Supports hot plug and un-plug detection and link status-failure detection
- HDCP compliant and Blu-ray ready
- Front panel push buttons for easy computer selection
- Rear panel FUNC button for easily adjusting the video signal strength (Depend on model)
- Buzzer sound for computer switching confirmation
- Hotkey functions allow easily computer access
- Supports existing VESA and Consumer Electronics Association (CEA) standards
- Screw-free design ,streamlined form factor for new all digital desktop monitors
- Complete interoperability
- Support Audio (Speaker + Mic); through HDMI Type A Female if CPU's audio sent with video over HDMI port

► Connection Pattern

