

UMHA-2 / UMHA-4



2 / 4 Port USB Console KVM Switch with Audio Function (SOHO Type)

► Specifications

| | | UMHA-2 | UMHA-4 |
|----------------------------|------------|----------------------------|-------------|
| Console Port Number | | 1 | |
| Computer Port Number | | 2 | 4 |
| Port Selection Push Button | | 1 | |
| Hot Plug-and-Play | | Yes | |
| Hot-Key Control | | Yes | |
| VGA Resolution | | 1920 x 1440, DDC2B Support | |
| Computer Interface | KB MS | USB Emulated or PS/2 | |
| | Monitor | HDB15 | |
| | Audio Jack | 2 sets | 4 sets |
| Console Interface | KB MS | USB Emulated | |
| | Monitor | HDB15 | |
| | Audio Jack | 1 set | |
| Automatic Scan Interval | | 3, 8, 15, 30 seconds | |
| KVM Cable Length | | 1.8mx2 | 1.8mx4 |
| Audio Cable Length | | 1.8mx4 | 1.8mx8 |
| H x W x D (mm) | | 20 x 182 x 87 | 35 x182 x87 |
| Power-Free Operation | | Yes | |

► Features

- Support USB & PS/2 Computer
- Unique loose-free cables included preventing keyboard or mouse connector from getting loose
- Supports USB console keyboard and mouse
- Keyboard and mouse emulation for error-free PC boot up
- Keyboard and mouse are hot pluggable at any time without turning either the UMH unit or PCs off
- Space-saving design - all cables are connected to the rear
- Auto scan automatically selects computers sequentially
- Supports M/S IntelliMouse (Pro), Explorer, Optical
- Hot-key and push button allow easy computer access
- Keyboard states automatically saved and restored when switching computers
- Operating system independent, transparent to all applications
- High VGA resolution 1920x1440
- Power-free operation - the UMH unit draws power from the attached PCs
- Support Stereo Audio & Microphone
- This Model Come With 2 or 4 1-to-2 USB Cable (Depends on Model)

► Connection Pattern



1-to-3 PS/2 Cable for PS/2 Computer



1-to-2 USB Cable for USB Computer

UMHA-2



UMHA-4

