

# XVA-G0808



8 x 8 VGA Matrix w/Audio

## ► Specifications

		XVA-G0808
Input Port	Video	HDB15-F x 8
	Audio	3.5mm Stereo Jack x 8
Output Port	Video	HDB15-F x 8
	Audio	3.5mm Audio Jack x 8
LEDs	Control Status	Dual Color x 4
	Port Selection	Yellow x 8 + Red x 8
Control	Push Button	8 + 4
	LAN	N/A
	Serial	DB9-F (DCE) x 1
	Remote	Remote Control Jack x 1
Resolution (Max.)	1920 x 1200, 1920 x 1440	
DDC2B	Support DDC1 & DDC2B for Plug & Play compatibility	
H x W x D (mm)	44 x 440 x 220	

## ► Features

- Routes 8 different VGA signals and audio sources to 8 different VGA monitors and speakers.
- Supports 1. Button front panel control  
2. Serial control  
3. IR remote control
- Front buttons for easy switching.
- Activates Auto Scan by front buttons pressing.
- Graphical User Interface (GUI) for easy and friendly operations
- Switches both of the video and audio directly
- Supports to turn ON/OFF the video and audio of each individual output port.
- Adjustable Volume for each audio port
- Programmable Scan / Display pattern
- Selectable Scan Time interval.
- Buzzer sound for switching confirmation.
- Supports video cascading to increase the capacity.
- Each output provides one video signal and one audio signal.
- Each input can be independently connected to any or all outputs.
- Supports the video resolution of WUXGA (1920 x 1200) / Full HD (1920x 1080) / UXGA (1600x 1200)
- Compatible with most of the popular screen resolution to XGA, SXGA, UXGA, WSXGA ... Full HD, WUXGA system.
- 1U-height form factor saves rack spaces

