

DADG-128D



8-Port Dual-View DVI KVM Switch w/ Audio and Hotkey Control

► Specifications

DADG-128D			
Console Port		1	
Computer Port		8	
Front Button		8	
Hot plug-and-play		Yes	
Automatic Scan Interval		3, 8, 15, 30, seconds	
Cable Length		3M (10ft) for USB	
Computer ON-LINE LED, (green)		8	
Computer Selected LED, (red)		8	
Computer Interface	KB	USB-B	
	MS		
	Monitor	DVI-Female	
	Audio Jack	Speaker+MIC	
Console Interface	KB	USB-A	
	MS		
	Monitor	DVI+VGA	
	Audio Jack	Speaker+MIC	
	USB Peripheral	USB-A	
OSD		Yes	
Hotkey		Yes	
Resolution		1920 x 1200 (WUXGA)	
DDC2B Support		Yes	
H x W x D (mm)		65 x 440 x 220 mm	
Power supply		Built-In AC100-240V	

► Features

- Completely controls with easy-to-use OSD interface
- Front panel push buttons and hotkey functions for easy computer selection
- Supports Dual-View function
- Supports EDID, HDCP, and is Blu-ray ready for high definition display
- Auto-scan function automatically selects computer sequentially
- Unique Tracking System enables audio devices to operate independently
- Assigns computers with unique and meaningful names
- Stores system settings and names entries to non-volatile memory
- Identifies and selects computers by the names
- Programmable scan filters unused computers
- Password security locks computer from unauthorized access
- Operating system independently and transparent to all applications
- Plug-and-Play system configuration
- DDC2B compatible
- Supports Windows and Mac host systems
- Compatible with most of the popular screen resolution to XGA, SXGA, UXGA, WSXGAFull HD, WUXGA system

► Connection Pattern

