

KAAG-114



4-Port VGA KVM Switch w/ Audio & Hotkey Control

Specifications

KAAG-114	
Console Port	1
Computer Port	4
Front Panel Push Button	4
Automatic Scan Interval	3, 8, 15, 30 Seconds
Cable Length (Max)	3M (10ft) for USB
Computer ON-LINE LED	4
Computer Selected LED	4
Hot Plug-and-Play	Yes
Console Interface	USB Port
	4 (KB+MS+Extra USB 2.0)
	KB
	USB
Computer Interface	MS
	USB
	Monitor
	VGA
Computer Interface	Audio Jack
	1 Set
	KB
	USB
Computer Interface	MS
	USB
Computer Interface	Monitor
	VGA
Computer Interface	Audio Jack
	4 Set
Hotkey	Yes
OSD	No
Resolution	UXGA(1600 x 1200), WUXGA(1920 x 1200)
DDC2B	Yes
H x W x D (mm)	44 x 220 x 130

Features

- Support Audio function
- Support USB console
- 4 computers share up to 4 different USB peripherals (KB + MS + USB 2.0 Devices)
- Unique Tracking System enable the USB devices to operate independently
- USB 2.0 peripheral sharing eliminates the expense of duplicate devices
- Front panel push buttons for easy computer selection
- No drivers needed for keyboard and mouse operation
- Support keyboard and mouse plug-n-play
- Buzzer sound for computer switching confirmation
- Hotkey functions allow easily computer access
- Activate Auto Scan by front buttons pressing
- Support Windows and Mac host systems
- No software required

Connection Pattern

